

倍利源

Braver Power

Features

- Small size and lightweight
- Intelligent automation control
- Soft-start design
- Programmable operation with 10-stage
- Change of output current and it is adjustable
- Inverter technology for energy-efficient
- Low ripple current
- Quick response
- High precision
- Can be connected to Analog / RS422 / RS485 / PLC
- Suitable for multi-machine synchronous operation

Functions

- Abnormal light display
- Over temperature & current display
- High/low voltage and current display
- 99 groups of programs for job selection
- C.C & C.V design
- AUTO mode

Applications

- Precious metals materials electroplating
- Precision electroplating
- Terminal continuous electroplating
- Passive element electroplating
- Printed circuit board
- Metals Coating
- Laboratory power supply

Custom designs available



Digital Pulse-Reverse ABU

Rated input voltage	220V, 1/3Φ; 380/440V, 3Φ ±15%
Phase	3Φ
Frequency	47~63 HZ
Rated input power	8.75 KVA
Average rated input current	28 Aac (+15%, -10%)
Output voltage range	0~25 Vdc
Output current range	0~250 Adc
Positive current /time	250A / 1~200ms
Negative current /time	250A / 1~200ms
C.C control accuracy	±3.0%
Pulse mode switching	Forward pulse / High - Low pulse / Positive Double Pulse / Pulse-Reverse Bi-polar Double Pulse

Standard chassis sizes available, also customizable upon request.

1 3U Cabinet



2 3U+High



3 Upright

